



THE DATASHEET OF

GP1A30R



GP1A30R

OPIC Photointerrupter with Encoder Function

■ Features

1. 2-phase (A, B) digital output
2. Possible to use plastic disk
3. High sensing accuracy
(Disk slit pitch : 0.7mm)
4. TTL compatible output
5. Compact and light

■ Applications

1. Electronic typewriters, printers
2. Numerical control machines

■ Absolute Maximum Ratings (Ta= 25°C)

Parameter		Symbol	Rating	Unit
Input	Forward current	I_F	65	mA
	*1Peak forward current	I_{FM}	1	A
	Reverse voltage	V_R	6	V
	Power dissipation	P	100	mW
Output	Supply voltage	V_{CC}	7	V
	Low level output current	I_{OL}	20	mA
	Power dissipation	P_O	250	mW
Operating temperature		T_{opr}	0 to + 70	°C
Storage temperature		T_{stg}	- 40 to + 80	°C
*2Soldering temperature		T_{sol}	260	°C

*1 Pulse width ≤ 100μs, Duty ratio= 0.01

*2 For 5 seconds

■ Electro-optical Characteristics

(Unless otherwise specified, Ta = 0 to + 70°C)

Parameter		Symbol	Conditions	MIN.	TYP.	MAX.	Unit
Input	Forward voltage	V_F	Ta= 25°C, I_F = 30mA	-	1.2	1.5	V
	Reverse current	I_R	Ta= 25°C, V_R = 3V	-	-	10	μA
Output	Operating supply voltage	V_{CC}		4.5	5.0	5.5	V
	High level output voltage	V_{OH}	*3 V_{CC} = 5V, I_F = 30mA	2.4	4.9	-	V
	Low level output voltage	V_{OL}	*3 I_{OL} = 8mA, V_{CC} = 5V, I_F = 30mA	-	0.1	0.4	V
	Supply current	I_{CC}	*3*4 I_F = 30mA, V_{CC} = 5V	-	5	20	mA
Transfer characteristics	Duty ratio	*5 D_A	V_{CC} = 5V, I_F = 30mA, *3f = 2.5kHz	20	50	80	%
		*5 D_B		20	50	80	%
	Response frequency	f_{MAX}	*3 V_{CC} = 5V, I_F = 30mA	-	-	5	kHz

*3 Measured under the condition shown in Measurement Conditions.


*4 In the condition that output A and B are low level.

*5

$$D_A = \frac{t_{AH}}{t_{AP}} \times 100, \quad D_B = \frac{t_{BH}}{t_{BP}} \times 100$$


■ Outline Dimensions

(Unit : mm)



*** OPIC™ (Optical IC) is a trademark of the SHARP Corporation.
An OPIC consists of a light-detecting element and signal-processing circuit integrated onto a single chip.

■ Output Waveforms



Rotational direction: Counterclockwise when seen from OPIC light detector

Fig. 1 Forward Current vs. Ambient Temperature




Fig. 2 Output Power Dissipation vs. Ambient Temperature




Fig. 3 Duty Ratio vs. Frequency




Fig. 4 Phase Difference vs. Frequency




Fig. 5 Duty Ratio vs. Ambient Temperature




Fig. 6 Phase Difference vs. Ambient Temperature




Fig. 7 Duty Ratio vs. Distance (X direction)




Fig. 8 Phase Difference vs. Distance (X direction)




Fig. 9 Duty Ratio vs. Distance (Y direction)




Fig.10 Phase Difference vs. Distance (Y direction)




Fig.11 Duty Ratio vs. Distance (Z direction)






Fig.12 Phase Difference vs. Distance (Z direction)



Measurement Conditions



Precautions for Use

- (1) This module is designed to be operated at $I_F = 30mA$ TYP.
- (2) Fixing torque : MAX. 0.6Nm (6kgf • cm)
- (3) In order to stabilize power supply line, connect a by-pass capacitor of more than $0.01\mu F$ between V_{CC} and GND near the device.
- (4) As for other general cautions, refer to the chapter "Precautions for Use".

<Basic Design>

R_O (distance between the disk center and half point of a slit),
 P (slit pitch), S_1 and S_2 (installing position of photointerrupter)
 will be provided by the following equations.

Slit pitch: P (slit center)


$$R_O = \frac{N}{120} \times 13.45 \text{ (mm)} \quad N: \text{number of slits}$$

$$P = \frac{2 \times p \times R_O}{N} \text{ (mm)}$$

$$S_1 = R_O - 1.765 \text{ (mm)}, S_2 = S_1 + 6.7 \text{ (mm)}$$

Note) When the number of slits is changed, values in parenthesis are also changed according to the number.

Enlarged drawing
 of A portion
 Slit pitch : P



(Ex.) In the case of
 $N = 200P/R$

$$R_O = \frac{200}{120} \times 13.45 \text{ (mm)}$$

$$= 22.42 \text{ mm}$$

$$P = \frac{2 \times p \times 22.42}{200} \text{ (mm)}$$

$$= 0.704 \text{ mm}$$

$$S_1 = 22.42 - 1.765$$

$$= 20.655 \text{ mm}$$

$$S_2 = 20.655 + 6.7$$

$$= 27.355 \text{ mm}$$

NOTICE

- The circuit application examples in this publication are provided to explain representative applications of SHARP devices and are not intended to guarantee any circuit design or license any intellectual property rights. SHARP takes no responsibility for any problems related to any intellectual property right of a third party resulting from the use of SHARP's devices.
- Contact SHARP in order to obtain the latest device specification sheets before using any SHARP device. SHARP reserves the right to make changes in the specifications, characteristics, data, materials, structure, and other contents described herein at any time without notice in order to improve design or reliability. Manufacturing locations are also subject to change without notice.
- Observe the following points when using any devices in this publication. SHARP takes no responsibility for damage caused by improper use of the devices which does not meet the conditions and absolute maximum ratings to be used specified in the relevant specification sheet nor meet the following conditions:
 - (i) The devices in this publication are designed for use in general electronic equipment designs such as:
 - Personal computers
 - Office automation equipment
 - Telecommunication equipment [terminal]
 - Test and measurement equipment
 - Industrial control
 - Audio visual equipment
 - Consumer electronics
 - (ii) Measures such as fail-safe function and redundant design should be taken to ensure reliability and safety when SHARP devices are used for or in connection with equipment that requires higher reliability such as:
 - Transportation control and safety equipment (i.e., aircraft, trains, automobiles, etc.)
 - Traffic signals
 - Gas leakage sensor breakers
 - Alarm equipment
 - Various safety devices, etc.
 - (iii) SHARP devices shall not be used for or in connection with equipment that requires an extremely high level of reliability and safety such as:
 - Space applications
 - Telecommunication equipment [trunk lines]
 - Nuclear power control equipment
 - Medical and other life support equipment (e.g., scuba).
- Contact a SHARP representative in advance when intending to use SHARP devices for any "specific" applications other than those recommended by SHARP or when it is unclear which category mentioned above controls the intended use.
- If the SHARP devices listed in this publication fall within the scope of strategic products described in the Foreign Exchange and Foreign Trade Control Law of Japan, it is necessary to obtain approval to export such SHARP devices.
- This publication is the proprietary product of SHARP and is copyrighted, with all rights reserved. Under the copyright laws, no part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, for any purpose, in whole or in part, without the express written permission of SHARP. Express written permission is also required before any use of this publication may be made by a third party.
- Contact and consult with a SHARP representative if there are any questions about the contents of this publication.

Looking for pricing, stock, or lifecycle information?

Click below to explore more details on WIN SOURCE:

- ⊖ View [GP1A30R](#) on WIN SOURCE
- ⊖ [Sharp Microelectronics](#) Information

Optimize Your Supply Chain with WIN SOURCE Solutions

- ✓ Global Sourcing Solution
- ✓ Obsolete Management
- ✓ Cost Control Management
- ✓ Shortage Management
- ✓ Alternative Solution
- ✓ Excess Inventory Management