

Errata Note

SX1272/73 – 860 to 1020 MHz Low Power Long Range Transceiver

Table of Contents

1	Chip Identification	2
2	LoRa Modem	3
2.1	<i>Frequency Offset Tolerance with 500 kHz Bandwidth</i>	3
2.2	<i>Receiver Spurious Reception</i>	3
2.3	<i>Valid Packet Counter Offset</i>	4
3	FSK Modem	5
3.1	<i>PayloadReady Set for 31.25ns if FIFO is Empty</i>	5
3.2	<i>Erroneous IBM Data Whitening/De-Whitening</i>	5
4	Revision History	6

1 Chip Identification

SX1272/73 is Production Released, with silicon Version V2b, identified as follows:

***RegVersion* at address 0x42 returns value 0x22**

This note describes the behavior of silicon Version V2b only.

Should you have any questions regarding the content of this document, or any other questions, please contact your Semtech sales representative.

Note:

Previous silicon revisions (V1a and V2a) are engineering samples which do not offer full functionality. They should not be used in a production device.

2 LoRa Modem

2.1 Frequency Offset Tolerance with 500 kHz Bandwidth

Description

With LoRa bandwidth set to 500 kHz, and with the largest spreading factors (SF=10,11,12), the tolerance to frequency offset is limited to +/-60 kHz

Workaround

No workaround identified.

2.2 Receiver Spurious Reception

Description

The SX1272/73 receiver shows spurious reception at a specific frequency offset. This may happen if a very high level LoRa signal is received at a specific offset, with the same bandwidth and spreading characteristic as the current modem settings:

Table 1: Default Spurious Rx Response

	LoRa BW Setting		
	125 kHz	250 kHz	500 kHz
Offset of Spurious Response	+/-1MHz	+/-2MHz	No response
Approximate max. level causing spurious reception (LoRa signal with same BW/SF)	-60dBm		

Workaround

The phenomenon can be mitigated by ~25dB by setting bit 7 at address 0x31 to 0. This bit is defaulted to 1 at POR or after a Manual Reset sequence, and should be set back to 0 after any of these events occur (during the radio initialization). The following performance is resulting:

Table 2: Optimized Rx Spurious Response

	LoRa BW Setting		
	125 kHz	250 kHz	500 kHz
Offset of Spurious Response	+/-1 MHz	+/-2 MHz	No response
Approximate max. level causing spurious reception (LoRa signal with same BW/SF)	-35dBm		

2.3 Valid Packet Counter Offset

Description

The valid packet counter (used for debug, and counting only packets whose CRC is correct) presents the following issue:

- In Rx Single mode, it does not increment
- In Rx Continuous mode, it does not count the first valid packet received

Workaround

- In Rx Single mode, do not use this counter, but instead increment a counter variable if *PayloadCrcError=0* on a *RxDone* interrupt.
- In Rx Continuous mode, the same method can apply.

3 FSK Modem

3.1 *PayloadReady* Set for 31.25ns if FIFO is Empty

Description

When receiving in Packet mode with the SX1272/73, the microcontroller can be instructed to service the FIFO and read the bytes it contains before the *PayloadReady* flag is set, thanks to the *FifoLevel* gauge. On the SX1272/73, the duration of *PayloadReady* is very short (31.25ns) if the FIFO is already emptied at packet end, when this interrupt fires.

This situation can happen if *FifoThreshold* and the corresponding *FifoLevel* interrupts are used to monitor the FIFO content and offload it on-the-go, *FifoThreshold* being equal to the number of bytes stored in the FIFO.

Workaround

When *FifoLevel* interrupt is used to offload the FIFO, the microcontroller should monitor both *PayloadReady* and *FifoLevel* interrupts, and read only (*FifoThreshold*-1) bytes off the FIFO when *FifoLevel* fires.

3.2 *Erroneous IBM Data Whitening/De-Whitening*

Description

On the SX1272/73, the implementation of the IBM-compatible whitening/de-whitening algorithm is erroneous, which makes it incompatible with the standard implementation.

Conditions:

- ✓ *CrcWhiteningType* = 1
- ✓ *DcFree* = 10

Workaround

The workaround is to use “unlimited Length Packet Format”, and process whitening/de-whitening in the host microcontroller. Semtech is providing software implementations of this algorithm. Please contact your Semtech representative for assistance.

4 Revision History

Revision	Date	Silicon Revision	Description/Changes
1	July 2013	V2b	First FINAL Revision

© Semtech 2013

All rights reserved. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner. The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice. No liability will be accepted by the publisher for any consequence of its use. Publication thereof does not convey nor imply any license under patent or other industrial or intellectual property rights. Semtech assumes no responsibility or liability whatsoever for any failure or unexpected operation resulting from misuse, neglect improper installation, repair or improper handling or unusual physical or electrical stress including, but not limited to, exposure to parameters beyond the specified maximum ratings or operation outside the specified range.

SEMTECH PRODUCTS ARE NOT DESIGNED, INTENDED, AUTHORIZED OR WARRANTED TO BE SUITABLE FOR USE IN LIFE-SUPPORT APPLICATIONS, DEVICES OR SYSTEMS OR OTHER CRITICAL APPLICATIONS. INCLUSION OF SEMTECH PRODUCTS IN SUCH APPLICATIONS IS UNDERSTOOD TO BE UNDERTAKEN SOLELY AT THE CUSTOMER'S OWN RISK. Should a customer purchase or use Semtech products for any such unauthorized application, the customer shall indemnify and hold Semtech and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs damages and attorney fees which could arise.

Contact Information

Semtech Corporation
Wireless and Sensing Products Division
200 Flynn Road, Camarillo, CA 93012
Phone: (805) 498-2111 Fax: (805) 498-3804
e-mail: support_rf@semtech.com

Looking for pricing, stock, or lifecycle information?

Click below to explore more details on WIN SOURCE:

-  [View SX1272IMLTRT on WIN SOURCE](#)
-  [Semtech Corporation](#) Information

Optimize Your Supply Chain with WIN SOURCE Solutions

-  Global Sourcing Solution
-  Obsolete Management
-  Cost Control Management
-  Shortage Management
-  Alternative Solution
-  Excess Inventory Management