



**THE DATASHEET OF
CSNK591-001**





Current Sensors Line Guide

Past, future, and current excellence. Honeywell Sensing and Control (S&C) offers a wide variety of current sensors to monitor alternating (ac) or direct (dc) current. From digital output detectors sensing a few hundred milliamps to linear sensors monitoring over one thousand amps, our comprehensive line provides superior, often accurate performance at a reduced cost.

As well as the advantages you'd expect from an experienced provider offering decades of engineering expertise: thru-hole design, fast response times, output voltage isolation from input, minimum energy dissipation, and enhanced reliability with adjustable performance and built-in temperature compensation.

FEATURES

DIGITAL/INDUCTIVE CURRENT SENSORS

CSDA Series.

Features: Open collector output • Digital output • ac or dc currents • Thru-hole design • Output voltage isolation from input • Minimum energy dissipation • Maximum current limited only by conductor size • Enhanced accuracy, low-cost sensing • RoHS compliant

Benefits: Single digital (TTL logic level, open collector) output that will sink 20 mA of output current. Provides logic level output that changes from Vcc to 0.4 V when sensed current exceeds the operate point. Will not be damaged by overcurrent in the sensed conductor. Potential applications include variable speed drives, overcurrent protection, ground fault detectors, current feedback control systems, robotics, UPS and telecommunication power supplies, welding power supplies, battery management systems, and wattmeters.

CLOSED LOOP CURRENT SENSORS

CSNB, CSNA, CSNC, CSNE, CSNF, CSNG, CSNJ, CSNK, CSNL, CSNM, CSNP, CSNR, CSNS, CSNT, and CSNX Series.

Features: Current sensing up to 1275 A • ac, dc, and impulse currents • In-line or thru-hole design • Competitive cost/performance ratio • Rapid response • Reduced overshoot • High overload capability • High level of electrical isolation between primary and secondary circuits • Industrial operating temperature range • Small size and weight • RoHS compliant • CE, UL approvals

Benefits: Based on the principles of the magnetoresistive or Hall effects, and the null balance or zero magnetic flux method (feedback system). Magnetic flux in the sensor core is constantly controlled at zero. Potential applications include variable speed drives, overcurrent protection, ground fault detectors, current feedback control systems, robotics, UPS and telecommunication power supplies, welding power supplies, battery management systems, and wattmeters.

OPEN LOOP CURRENT SENSORS CSCA-A Series.

Features: ac, dc, and impulse currents • Competitive cost/performance ratio • Low power consumption • Compact size • High level of electrical isolation between primary and secondary circuits • Large primary aperture • RoHS compliant • CE, UL approvals

Benefits: Based on the principles of the Hall-effect wherein a Hall-effect device (HED) produces an output voltage linearly related to the amplitude and phase of a magnetic field applied to it. HED output is directly proportional to the amplitude and phase of the primary current. Potential applications include variable speed drives, overcurrent protection, ground fault detectors, current feedback control systems, robotics, UPS and telecommunication power supplies, welding power supplies, battery management systems, and wattmeters.

Current Sensors Line Guide

Common sense. Global leadership.

Honeywell S&C offers linear (analog) open loop, digital, or closed-loop current sensors. When any of these sensors detect predetermined signals, the system then performs the designated task. For instance, the digital signal's logic level output may sound an alarm, start a motor, or open a valve. The linear signal duplicates the waveform — often ideal for feedback elements to control a motor, or regulate machine function. And Honeywell's new closed-loop current sensor with magnetoresistive (MR) technology offers amazing offset drift performance over a wide temperature range — with almost no thermal drift, for enhanced accuracy.

For proven engineering expertise, component dependability, and global support, trust Honeywell S&C.



Digital/Inductive Current Sensors

CSDA Series

Operate current	0.5 A.t. nom., 3.5 A.t. nom.
Sensed current type	ac or dc
Output	voltage
Response time	100 μ s
Accuracy	better than 0.5 %
Mounting	PCB mounting pins or screw mount
Pinout style	3-pin PCB or 3-pin AMP connector
Operating temperature	-25 °C to 85 °C [-13 °F to 185 °F]
Supply voltage	6 Vdc to 16 Vdc



Closed Loop Current Sensors

CSNX Series

CSNA Series

CSNF Series

Sensed current range	± 56 A	± 70 A, ± 90 A, ± 100 A	± 150 A, ± 180 A, ± 200 A
Sensed current type	ac, dc, impulse	ac, dc, impulse	ac, dc, impulse
Output	current	current	current
Coil turns	2000 (50 Ohm coil)	1000 (90 or 50 Ohm coil) 2000 (160 or 130 Ohm coil)	1000 (30 Ohm coil) 2000 (100 Ohm coil)
Response time	< 0.2 μ s	< 1 μ s	< 0.5 μ s
Accuracy	± 0.24 %	± 0.5 %	± 0.5 %
Mounting	PCB on 11-pins	PCB on 3-pins	PCB on 3-pins
Pinout style	unipolar	offset	center
Operating temperature	-40 °C to 85 °C [-40 °F to 185 °F]	0 °C to 70 °C [32 °F to 158 °F]	-40 °C to 85 °C [-40 °F to 185 °F]
Supply voltage	4.75 Vdc to 5.25 Vdc	± 13 Vdc, ± 15 Vdc	± 12 Vdc to ± 15 Vdc




Closed Loop Current Sensors

CSNB Series

CSNC Series

CSNE Series

Sensed current range	±100 A	±90 A	±36 A, ±90 A
Sensed current type	ac, dc	ac, dc	ac, dc, impulse
Output	current	current	current
Coil turns	2000	1000 (50 Ohm coil)	1000 (110 Ohm or 66 Ohm coil)
Response time	< 1 µs	< 1 µs	< 1 µs
Accuracy	±0.5 %	±0.5 %	±0.5 %
Mounting	PCB on 3 pins	PCB on 3 pins	PCB on 13 pins
Pinout style	Offset	Offset	5-pin
Operating temperature	0 °C to 70 °C [32 °F to 158 °F]	-25 °C to 85 °C [-13 °F to 185 °F]	0 °C to 70 °C [32 °F to 158 °F]
Supply voltage	±15.0 Vdc	±13.0 Vdc	±12 Vdc to ±15 Vdc



Closed Loop Current Sensors

CSNG Series

CSNJ Series

CSNK Series

Sensed current range	±180 A, ±200 A	±600 A	±1200 A
Sensed current type	ac, dc	ac, dc, impulse	ac, dc, impulse
Output	current	current	current
Coil turns	2000	2000	5000 (50 Ohm coil)
Response time	< 0.5 µs	< 0.5 µs	< 1 µs
Accuracy	±0.5 %	±0.5 %	±0.5 %
Mounting	PCB on 3 pins	panel	panel
Pinout style	offset	spade terminals (x 3)	Molex (3-way)
Operating temperature	-40 °C to 85 °C [-40 °F to 185 °F]	-40 °C to 85 °C [-40 °F to 185 °F]	-40 °C to 85 °C [-40 °F to 185 °F]
Supply voltage	±15.0 Vdc	±12.0 Vdc to ±18.0 Vdc	±15 Vdc to ±18 Vdc

Current Sensors Line Guide



Closed Loop Current Sensors

CSNL Series

CSNM Series

CSNP Series

Sensed current range	±600 A	±1000 A	±90 A
Sensed current type	ac, dc	ac, dc	ac, dc
Output	current	current	current
Coil turns	2000	3000	1000
Response time	< 0.5 μ s	< 1 μ s	< 0.5 μ s
Accuracy	±0.5 %	±0.5 %	±0.5 %
Mounting	panel	panel	PCB on 3 pins
Pinout style	Molex (3-way)	Molex (3-way)	offset
Operating temperature	-40 °C to 85 °C [-40 °F to 185 °F]	-40 °C to 85 °C [-40 °F to 185 °F]	-40 °C to 85 °C [-40 °F to 185 °F]
Supply voltage	±12.0 Vdc to ±18.0 Vdc	±12.0 Vdc to ±18.0 Vdc	±12.0 Vdc to ±15.0 Vdc



Closed Loop Current Sensors

CSNS Series

CSNR Series

CSNT Series


Sensed current range	±320 A, ±600 A	±200 A	±150 A
Sensed current type	ac, dc, impulse	ac, dc	ac, dc
Output	current	current	current
Coil turns	2000	1000, 2000	2000
Response time	< 0.5 μ s	< 0.5 μ s	< 0.5 μ s
Accuracy	±0.5 %	±0.5 %	±0.5 %
Mounting	panel	PCB on 3 pins	PCB on 3 pins
Pinout style	Molex (3-way)	center, offset	offset
Operating temperature	-40 °C to 85 °C [-40 °F to 185 °F]	-40 °C to 85 °C [-40 °F to 185 °F]	-40 °C to 85 °C [-40 °F to 185 °F]
Supply voltage	±12 Vdc to ±18 Vdc	±12.0 Vdc to ±15.0 Vdc	±12.0 Vdc to ±15.0 Vdc



Open Loop Current Sensors

	CSCA-A Series	CSLA Series	CSLH Series
Sensed current range	±150 A, ±300 A ±600 A, ±900 A	±57 A to ±950 A	±9 A, ±45 A
Sensed current type	ac, dc, impulse	ac, dc	ac, dc
Output	voltage	voltage	sink/source
Response time	3 μs to 7 μs	3 μs, 8 μs	3 μs
Sensitivity	–	various	18.5 mV N* ±3.5 mV N* @ 5 Vdc or 282 mV N* -42, +82 mV N* @ 10 Vdc
Mounting	Molex connector Gallant connector	PCB on 3-pins	PCB on 3-pins
Pinout style	–	3-pin	3-pin
Operating temperature	-10 °C to 80 °C [14 °F to 176 °F]	-25 °C to 85 °C [-13 °F to 185 °F]	-25 °C to 85 °C [-13 °F to 185 °F]
Supply voltage	±15 Vdc ±5 %	8 Vdc to 16 Vdc 6 Vdc to 12 Vdc	4.5 Vdc to 10.5 Vdc

N = Number of turns



Open Loop Current Sensors

	CSLS Series	CSLT Series	CSLW Series
Sensed current range	±60 A	±100 A	±1 A, ±5 A, ±40 mA, ±200 mA
Sensed current type	ac, dc	ac, dc	ac, dc
Output	sink/source	sink/source	sink/source
Coil turns	–	–	12, 60, 300, 1500
Response time	3 μs	3 μs	3 μs
Sensitivity	15 mV/AT ±2 mV/AT @ 5 Vdc	15 mV/AT ±2 mV/AT @ 5 Vdc	various
Mounting	PCB	PCB	PCB
Pinout style	3-pin	3-pin	5-pin
Operating temperature	-25 °C to 100 °C [-13 °F to 212 °F]	-25 °C to 100 °C [-13 °F to 212 °F]	-25 °C to 100 °C [-13 °F to 212 °F]
Supply voltage	4.5 Vdc to 10.5 Vdc	4.5 Vdc to 10.5 Vdc	4.5 Vdc to 10.5 Vdc

CSLA Series.

Features: Linear output • ac or dc currents • Thru-hole design • Enhanced response time • Output voltage isolation from input • Minimum energy dissipation • Maximum current limited only by conductor size • Adjustable performance and built-in temperature compensation assures reliable operation • Enhanced accuracy, low-cost sensing • RoHS compliant

Benefits: Incorporates Honeywell's 91SS12-2 and SS94A1 linear output Hall-effect transducer (LOHET™). Sensing element is assembled in a printed circuit board mountable housing, available in four configurations. Potential applications include variable speed drives, overcurrent protection, ground fault detectors, current feedback control systems, robotics, UPS and telecommunication power supplies, welding power supplies, battery management systems, and wattmeters.

CSLH Series.

Features: ac or dc currents • Miniature • Linear ratiometric output • Current sinking or sourcing output for interfacing flexibility • No insertion loss • Enhanced response time • Low-cost sensing • Minimum energy dissipation • Maximum current limited only by conductor size • Built-in temperature compensation promotes reliable operation • RoHS compliant

Benefits: Open-loop sensor incorporates Honeywell's SS490 Series miniature ratiometric linear Hall-effect sensor. Element is encapsulated in a PCB-mountable plastic package. Combination of sensor, flux collector, and housing comprises the current sensor assembly. Potential applications include motor control, HVAC and consumer tools, current monitoring of electronic circuits, overcurrent protection, ground fault

detectors, robotics, industrial process control, UPS and telecommunication power supplies, welding current monitoring, battery management systems in mobile equipment, watt meters, and variable speed drives.

CSLS, CSLT, CSLW Series.

Features: ac or dc currents • Linear ratiometric output • Current sinking or sourcing output for interfacing flexibility • No insertion loss • Enhanced response time • Compact size for applications with limited space • Enhanced accuracy, low-cost sensing • Minimum energy dissipation • Maximum current limited only by conductor size • Built-in temperature compensation promotes reliable operation • RoHS compliant

Benefits: Incorporate Honeywell's SS490 Series miniature ratiometric linear Hall-effect sensor. Element is encapsulated in a printed circuit board-mountable plastic package. Sensors are ratiometric. Potential applications include motor control in HVAC and consumer tools, current monitoring of electronic circuits, overcurrent protection, ground fault detectors, robotics, industrial process control, UPS and telecommunication power supplies, welding current monitoring, battery management systems in mobile equipment, watt meters, and variable speed drives.

Warranty. Honeywell warrants goods of its manufacture as being free of defective materials and faulty workmanship. Honeywell's standard product warranty applies unless agreed to otherwise by Honeywell in writing; please refer to your order acknowledgement or consult your local sales office for specific warranty details. If warranted goods are returned to Honeywell during the period of coverage, Honeywell will repair or replace, at its option, without charge those items it finds

defective. **The foregoing is buyer's sole remedy and is in lieu of all warranties, expressed or implied, including those of merchantability and fitness for a particular purpose. In no event shall Honeywell be liable for consequential, special, or indirect damages.**

While we provide application assistance personally, through our literature and the Honeywell web site, it is up to the customer to determine the suitability of the product in the application.

Specifications may change without notice. The information we supply is believed to be accurate and reliable as of this printing. However, we assume no responsibility for its use.

For more information about Sensing and Control products, visit www.honeywell.com/sensing or call +1-815-235-6847. Email inquiries to info.sc@honeywell.com

WARNING **PERSONAL INJURY**

- DO NOT USE these products as safety or emergency stop devices or in any other application where failure of the product could result in personal injury.

Failure to comply with these instructions could result in death or serious injury.

WARNING **MISUSE OF DOCUMENTATION**

- The information presented in this catalogue is for reference only. DO NOT USE this document as product installation information.
- Complete installation, operation and maintenance information is provided in the instructions supplied with each product.

Failure to comply with these instructions could result in death or serious injury.

Sensing and Control
Automation and Control Solutions
Honeywell
1985 Douglas Drive North
Golden Valley, MN 55422 USA
+1-815-235-6847
www.honeywell.com/sensing

005895-1-EN IL50 GLO
June 2008
Copyright © 2008 Honeywell International Inc. All rights reserved.

Honeywell

Looking for pricing, stock, or lifecycle information?

Click below to explore more details on WIN SOURCE:

 [View CSNK591-001 on WIN SOURCE](#)

 [Honeywell Information](#)

Optimize Your Supply Chain with WIN SOURCE Solutions

-  Global Sourcing Solution
-  Obsolete Management
-  Cost Control Management
-  Shortage Management
-  Alternative Solution
-  Excess Inventory Management