

Security Advisory

Title	Security Advisory for USB_OTG & USB_Serial_JTAG Download Functions of ESP32-S3 Series Products
Issue date	2022/12/21
Advisory Number	AR2022-004
Serial Number	NA
Version	V1.1

Issue Summary

ESP32-S3 features a USB On-The-Go (OTG) interface which complies with the USB 2.0 specification. It supports downloading firmware through USB module. For more information, please refer to [Device Firmware Upgrade Through USB](#). For ESP32-S3 series chips manufactured before Date Code 2219¹ and modules and development boards with the PW No. before PW-2022-06-XXXX, the **EFUSE_DIS_USB_OTG_DOWNLOAD_MODE (BLK0 B19[7]²)** bit of eFuse is set by default and cannot be modified. Therefore, the USB_OTG Download function is unavailable for these products.

Note: This bit (**BLK0 B19[7]**) was defined as **EFUSE_ERR_RST_ENABLE** in previous versions of *ESP32-S3 Technical Reference Manual* and ESP-IDF, and it has been redefined as **EFUSE_DIS_USB_OTG_DOWNLOAD_MODE** in the latest version.

ESP32-S3 also supports downloading firmware through USB_Serial_JTAG. Please refer to [Uploading the Application via USB-Serial-JTAG](#). Users can set **EFUSE_DIS_USB_SERIAL_JTAG_DOWNLOAD_MODE (BLK0 B16[4])** to disable this feature.

Note: This bit (**BLK0 B16[4]**) was defined as **EFUSE_DIS_USB_DOWNLOAD** in previous versions of *ESP32-S3 Technical Reference Manual* and ESP-IDF, and it has been updated in the latest version.

¹ 2219: Indicates the 19th week of the year 2022. D/C on chip product labels is marked as 2219 (YYWW) and Date Code on chip product silk markings is marked as 192022 (WWYYYY). Please refer to [Espressif Chip Packaging Information](#). Similarly hereinafter.

² BLK0 B19[7]: Indicates the 7th bit of the 19th byte in Block0 of eFuse memory. Similarly hereinafter.

Updates

For ESP32-S3 series chips manufactured on and after Date Code 2219 and modules and development boards with the PW No. of and after PW-2022-06-XXXX, the bit (**BLK0 B19[7]**) will be open for users to program since it will not be programmed by default. This will enable the USB_OTG Download function.

EFUSE_DIS_USB_DOWNLOAD_MODE (BLK0 B16[4]) can only be used to disable USB_Serial_JTAG Download. In the latest version of ESP-IDF, it has been renamed **EFUSE_DIS_USB_SERIAL_JTAG_DOWNLOAD_MODE**.

Recommendations for Users

- **Security Recommendations for Using USB_OTG of the ESP32-S3 Series Products After the Updates**

Recommendations for firmware security-sensitive users:

1. For ESP32-S3 series products, the USB_OTG Download function will be disabled if any of the **EFUSE_ENABLE_SECURITY_DOWNLOAD**, **EFUSE_DIS_USB_OTG**, or **EFUSE_DIS_DOWNLOAD_MODE** is programmed. In such circumstance, this security advisory can be ignored.
2. For ESP32-S3 series products manufactured on and after Date Code 2219, if none of the **EFUSE_ENABLE_SECURITY_DOWNLOAD**, **EFUSE_DIS_USB_OTG**, and **EFUSE_DIS_DOWNLOAD_MODE** bits are programmed in the product manufacturing process, users should additionally program the **EFUSE_DIS_USB_OTG_DOWNLOAD_MODE** bit to disable the USB_OTG Download feature during the manufacturing. This will protect the firmware from unauthorized access or malicious attacks via USB_OTG.

- **Security Recommendations for Using USB_Serial_JTAG Download of the ESP32-S3 Series Products After the Updates**

The **EFUSE_DIS_USB_SERIAL_JTAG_DOWNLOAD_MODE** bit should be programmed separately to protect the firmware from unauthorized access or malicious attacks via USB_Serial_JTAG.

Note: The bit was defined as **EFUSE_DIS_USB_DOWNLOAD_MODE** previously, but it only disables USB_Serial_JTAG Download. If there is a need to disable USB_OTG Download, please program **EFUSE_DIS_USB_OTG_DOWNLOAD_MODE** according to the above recommendation.

If you need technical assistance, please contact [Espressif](https://www.espressif.com).

Revision History

Date	Version	Release notes
2022/12/21	V1.1	Added chip product date code description.
2022/06/01	V1.0	Initial release.

Looking for pricing, stock, or lifecycle information?

Click below to explore more details on WIN SOURCE:

- ⊖ [View ESP32-S3-DEVKITM-1-N8 on WIN SOURCE](#)
- ⊖ [Espressif Information](#)

Optimize Your Supply Chain with WIN SOURCE Solutions

- ✓ Global Sourcing Solution
- ✓ Obsolete Management
- ✓ Cost Control Management
- ✓ Shortage Management
- ✓ Alternative Solution
- ✓ Excess Inventory Management