



THE DATASHEET OF FMS1



Opticom® Rack Mount Fiber Enclosures

specifications

Rack mount fiber enclosures shall house, organize, manage and protect fiber optic cable, terminations, splices, connectors and patch cords. Enclosure shall accommodate all Panduit trunk cables, connectors, patch cords, fiber adapter panels (FAP) and fiber mount panels (FMP). The enclosure shall include integral cable management and bend radius control for transition to vertical cable managers. Fiber optic enclosures shall be constructed of steel material. Molded front and back doors shall be removable for cabling and connector installation. 1 RU and 2 RU enclosures shall provide full front and rear access with a drawer that slides forward and backward. 3 RU and 4 RU enclosures shall feature a fixed bulkhead design. Enclosure shall have multiple knockouts for a variety of trunk cable entry points.



technical information

Dimensions:	FRME1U: 1.74"H x 17.38"W x 14.2"D (44mm x 441.5mm x 361mm), 1 RU
	FRME2U: 3.48"H x 17.38"W x 14.2"D (88mm x 441.5mm x 361mm), 2 RU
	FRME3: 5.00"H x 17.0"W x 11.8"D (127mm x 432mm x 299mm), 3 RU
	FRME4: 6.62"H x 17.0"W x 11.8"D (168mm x 432mm x 299mm), 4 RU
Mounting:	Universal brackets (included) allow enclosure to fit in 19" or 23" rack
Accessories:	Mounting hardware and accessory kit with labels included

key features and benefits

Works with all Panduit® Opticom® LC, SC, ST, MT-RJ and MTP* Connector Fiber Adapter Panels	Provides versatility and flexibility with a fully modular solution for a variety of fiber optic patching, terminating, and splicing applications
Integral cable management	Provides proper cable routing pathways and ensures minimum cable bend radius for end-to-end signal integrity
Bi-directional pullout drawers (FRME1U and FRME2U)	Improves front access to patch cords and connectors and rear access to terminations, slack storage and trunk cable/inter-connect cables; faster and easier installation for lower total installed cost and reduced maintenance costs
Hinged, removable front and rear doors	Enables access to fiber optic patch cords without needing to move drawer for easier moves, adds, and changes
One-to-one patching and splicing capability (FRME1U and FRME2U)	Yields higher port densities for fusion splice applications with one-to-one patching-to-splicing fiber count for up to 72 splices per RU
TIA-606-A compatible labeling	Standards-based, mechanically printed labeling of fiber connectivity, patchfields, and enclosures enables clear and accurate labeling for easy moves, adds and changes

applications

Opticom® Rack Mount Fiber Enclosures provide a flexible system suitable for managing fiber terminations, connections, and patching in all types of applications. The enclosure can serve as a transition from backbone cabling to distribution switching in telecommunications rooms or closets, an interconnect to active equipment in server cabinets or switch racks, or can be specified for cross-connect or inter-connect use in a main distribution area or horizontal distribution area.

The enclosures can manage from 12 to 72 fibers in 1 RU and up to 288 fibers in 4 RU when used with standard FAP and FMP series adapter panels loaded with LC, SC, ST, MT-RJ, or MTP* style adapters. Integral cable management, bend radius control, and slack management features protect fiber optic cables, patch cords, and connectors ensuring end-to-end signal integrity for increased network reliability.

*MTP is a registered trademark of US Conec Ltd.

Opticom® Rack Mount Fiber Enclosures

3 FAP openings (72 fibers, 1 RU):	FRME1U
6 FAP openings (144 fibers, 2 RU):	FRME2U
9 FAP openings (216 fibers, 3 RU):	FRME3
12 FAP openings (288 fibers, 4 RU):	FRME4

Opticom® Fiber Adapter Panels

12 duplex LC, 10Gig™:	FAP12WAQDLCZ
6 duplex LC, 10Gig™:	FAP6WAQDLCZ
12 duplex LC:	FAP12WEIDLC
6 duplex LC:	FAP6WEIDLC
6 duplex SC, 10Gig™:	FAP6WAQDSCZ
3 duplex SC, 10Gig™:	FAP3WAQDSCZ
6 duplex SC:	FAP6WEIDSC
3 duplex SC:	FAP3WEIDSC
6 simplex ST:	FAP6WST
6 duplex MT-RJ:	FMP6WMTRJ
MPO/MTP*:	FAP4WBLMTP
MPO/MTP*:	FAP6WBLMTP

Splice Modules (For Use with FRME1U and FRME2U Only)

Splice module (fusion):	FOSMF
Splice module (mechanical):	FOSMM

Tools and Accessories


Panduit connector removal tool:	PCRT1
Fiber slack spool 1 RU:	FMS1
Fiber slack spool 2 RU:	FMS2
Bend radius clip:	FEBRC

Opticom® Rack Mount Fiber Enclosures

Fiber Capacities

Fiber Adapter Panel Type	Enclosure and Fiber Count			
	FRME1U (holds up to 3 FAPs)	FRME2U (holds up to 6 FAPs)	FRME3 (holds up to 9 FAPs)	FRME4 (holds up to 12 FAPs)
Twelve duplex LC adapters	72	144	216	288
Eight duplex LC adapters	48	96	144	192
Six duplex LC adapters	36	72	108	144
Six duplex SC adapters	36	72	108	144
Four duplex SC adapters	24	48	72	96
Three duplex SC adapters	18	36	54	72
Eight simplex ST adapters	24	48	72	96
Six simplex ST adapters	18	36	54	72
Six duplex MT-RJ adapters	36	72	108	144
Six simplex FC adapters	18	36	54	72

Opticom® Rack Mount Fiber Enclosures



Dimensions are in inches (Dimensions in parentheses are metric).

WORLDWIDE SUBSIDIARIES AND SALES OFFICES

PANDUIT CANADA
Markham, Ontario
cs-cdn@panduit.com
Phone: 800.777.3300

PANDUIT EUROPE LTD.
London, UK
cs-emea@panduit.com
Phone: 44.20.8601.7200

PANDUIT SINGAPORE PTE. LTD.
Republic of Singapore
cs-ap@panduit.com
Phone: 65.6305.7575

PANDUIT JAPAN
Tokyo, Japan
cs-japan@panduit.com
Phone: 81.3.6863.6000

PANDUIT LATIN AMERICA
Jalisco, Mexico
cs-la@panduit.com
Phone: 52.33.3777.6000

PANDUIT AUSTRALIA PTY. LTD.
Victoria, Australia
cs-aus@panduit.com
Phone: 61.3.9794.9020

For a copy of Panduit product warranties, log on to www.panduit.com/warranty

For more information

Visit us at www.panduit.com



Contact Customer Service by email: cs@panduit.com
or by phone: 800-777-3300

PANDUIT®

©2016 Panduit Corp.
ALL RIGHTS RESERVED.
FBSP119--WW-ENG
12/2016

Looking for pricing, stock, or lifecycle information?

Click below to explore more details on WIN SOURCE:

-  [View FMS1 on WIN SOURCE](#)
-  [Panduit Corp](#) Information

Optimize Your Supply Chain with WIN SOURCE Solutions

-  Global Sourcing Solution
-  Obsolete Management
-  Cost Control Management
-  Shortage Management
-  Alternative Solution
-  Excess Inventory Management