



# THE DATASHEET OF FSM500LCF



# DATA SHEET

## Hall Effect Current Sensor

**P/N: FSM200L2F**

**$I_{PN} = \pm 200A$**

### Feature


- Closed- loop (compensated) current transducer
- Capable measurement of currents: DC, AC, pulse with galvanic isolation between primary circuit and secondary circuit.
- Supply voltage: DC  $\pm 12 \sim 15V$

### Advantages

- High accuracy
- Low temperature drift
- Optimized response time
- Very good linearity
- High immunity to external interference

### Applications

- The application of variable frequency electrical appliances
- AC/DC variable-speed drive
- Uninterruptible Power Supplies (UPS)
- Switched Mode Power Supplies (SMPS)
- The applications of inverter



**RoHS**

### Electrical data: ( $T_A = 25^\circ C$ , $V_C = \pm 15VDC$ )

Parameter Ref	FSM200L2F	
Rated input $I_{PN}(A)$	$\pm 200$	
Measuring range $I_P(A)$	$0 \sim \pm 500$	
Turns ratio NP/NS (T)	1 : 2000	
Output current $I_S (mA)$	$\pm 100 * I_P / I_{PN}$	
Secondary coil resistance $R_S(\Omega)$	@ $T_A = + 25^\circ C$	21.0
	@ $T_A = + 85^\circ C$	25.0
Inside resistance $R_M(\Omega)$	@ $T_A = + 85^\circ C$	$[(V_C - 0.6V) / (I_S * 0.001)] - R_S$ max
Supply voltage $V_C(V)$	$(\pm 12 \sim \pm 15) \pm 5\%$	
Accuracy $X_G(\%)$	@ $I_{PN}, T = 25^\circ C$	$< \pm 0.5$
Offset current $I_{OE}(mA)$	@ $I_P = 0, T = 25^\circ C$	$< \pm 0.2$
Temperature variation of $I_{OE} (mA)$	@ $I_P = 0, -40 \sim +85^\circ C$	TYP $< \pm 0.12$ MAX $< \pm 0.40$
Magnetic offset current $I_{OH} (mA)$	@ $I_P = 0 \rightarrow 3 * I_{PN}$	$< \pm 0.1$
Linearity error $\epsilon_r(\%FS)$	$< 0.1$	
Di/dt accurately followed ( $A/\mu s$ )	$> 100$	
Response time $t_{ra}(\mu s)$	@ 90% of $I_{PN}$	$< 1.0$
Power consumption $I_C(mA)$	@ $\pm 15V$	$17 + I_S$

Bandwidth BW (KHZ)	@-3dB, IPN	DC-100
Insulation voltage Vd(KV)	@50/60Hz, 1min, AC	6.0

**General data:**

Parameter	Value
Operating temperature $T_A(^{\circ}C)$	-40 ~ +85
Storage temperature $T_S(^{\circ}C)$	-55 ~ +125
Mass M(g)	78
Plastic material	PBT G30/G15, UL94- V0;
Standards	IEC60950-1:2001
	EN50178:1998
	SJ20790-2000

**Dimensions(mm):**

**Connection**

**General tolerance**

General tolerance:  $< \pm 0.5\text{mm}$

Primary through-hole:  $D 15.6 \pm 0.50\text{mm}$

Connection of Secondary: MOLEX 39-28-8040(old part number:5566-04A-210)

**Remarks:**

- When the current goes through the primary pin of a sensor, the voltage will be measured at the output end.
- Custom design is available for the different rated input current and the output voltage.
- The dynamic performance is the best when the primary hole is fully filled with.

**WARNING : Incorrect wiring may cause damage to the sensor.**

## Looking for pricing, stock, or lifecycle information?

Click below to explore more details on WIN SOURCE:

- [⊖ View FSM500LCF on WIN SOURCE](#)
- [⊖ Shanghai Freesor Sensor Technology Co.,Ltd Information](#)

## Optimize Your Supply Chain with WIN SOURCE Solutions

- ✓ Global Sourcing Solution
- ✓ Obsolete Management
- ✓ Cost Control Management
- ✓ Shortage Management
- ✓ Alternative Solution
- ✓ Excess Inventory Management