




**THE DATASHEET OF
PT6305CT**



PT6305 Series

**3 AMP HIGH-PERFORMANCE
ADJUSTABLE ISR**




- Single-Device 5V to 3V Power
- 85% Efficiency
- Small SIP Footprint:
0.36" x 2.00" x 0.60"(H)
- Wide Input Voltage Range:
+4.5V to +9.0V
- Internal Short Circuit Protection
- Over-Temperature Protection

The PT6305N is Power Trends' new high performance +5V to +3.3V, 3


Amp, 12-Pin SIP (Single In-line-Package) Integrated Switching Regulator (ISR). This high-performance ISR allows easy integration of low-power 3.3V logic IC's into existing 5V systems without redesigning the central power supply. Only one external capacitor is required for proper operation. The PT6306,7,8 can be used to power high-speed data buses (+2.1V), or the new GTL (+1.2V) logic buses.

Standard Application



Pin-Out Information

Pin No.	Function	Pin No.	Function
1	N/C	7	GND
2	V_{in}	8	GND
3	V_{in}	9	V_{out}
4	V_{in}	10	V_{out}
5	GND	11	V_{out}
6	GND	12	Adjust (See page 40.)



Ordering Information

- PT6305□ = +3.3 Volts
- PT6306□ = +1.8 Volts
- PT6307□ = +2.1 Volts
- PT6308□ = +1.2 Volts
(For dimensions, see page 66.)

PT Series Suffix (PT1234X)

Case/Pin Configuration	Heat Tab Configuration	
	None	Side
Vertical Through-Hole	N	R
Horizontal Through-Hole	A	G
Horizontal Surface Mount	C	B

(See Thermal Application Notes on page 44 for heat tab application data.)

Specifications

Characteristics ($T_a=25^\circ\text{C}$ unless noted)	Symbols	Conditions	PT6305 SERIES				
			Min	Typ	Max	Units	
Output Current	I_o	$4.5 \leq V_{in} \leq V_{in\ MAX}$	0.3	—	3.0**	ADC	
Current Limit	I_{cl}	$V_{in} = +5V$	—	3.6	5.0	ADC	
Short Circuit Current	I_{sc}	$V_{in} = +5V$	—	5.0	—	Apk	
Input Voltage Range	V_{in}	$0.3A \leq I_o \leq 3.0A$	PT6305N PT6306N PT6307N PT6308N	4.5 4.5 4.5 4.5	— — — —	9 9 9 6.0	VDC VDC VDC VDC
Static Voltage Tolerance	V_o	$V_{in} = +5V, I_o = 3.0A$ $0^\circ\text{C} \leq T_a \leq +70^\circ\text{C}$	PT6305N PT6306N PT6307N PT6308N	3.2 1.7 2.0 1.1	3.3 1.8 2.1 1.2	3.4 1.9 2.2 1.3	VDC VDC VDC VDC
Line Regulation	Reg_{line}	$4.5V \leq V_{in} \leq 5.5V, I_o = 3.0A$	—	± 25	± 50	—	mV
Load Regulation	Reg_{load}	$V_{in} = +5V, 0.3 \leq I_o \leq 3.0A$	—	± 25	± 50	—	mV
V_o Ripple/Noise pk-pk	V_n	$V_{in} = 5V, I_o = 3.0A$	—	66	—	—	mV
Transient Response with $C_2 = 100\mu\text{F}$	t_{tr} V_{os}	I_o step between 1.5A and 3.0A V_o over/undershoot	— —	200 200	— —	— —	μSec mV
Efficiency	η	$V_{in} = +5V, I_o = 1.5A$	PT6305N PT6306N PT6307N PT6308N	— — — —	85 74 77 63	— — — —	% % % %
		$V_{in} = +5V, I_o = 3.0A$	PT6305N PT6306N PT6307N PT6308N	— — — —	80 68 72 57	— — — —	% % % %
Switching Frequency	f_o	$4.5 \leq V_{in} \leq V_{in\ MAX}$ $0.3A \leq I_o \leq 3.0A$	—	500	650	800	KHz
Operating Temperature	T_a	Free Air Convection (40-60 LFM) Over V_{in} and I_o Ranges	—	0	—	+70*	$^\circ\text{C}$
Thermal Resistance	θ_{ja}	Free Air Convection (40-60 LFM)	—	25	—	—	$^\circ\text{C}/\text{W}$
Storage Temperature	T_s	—	—	-40	—	+125	$^\circ\text{C}$
Mechanical Shock		Per Mil-STD-883D, Method 2002.3 Condition A, 1 msec, Half Sine, mounted to a fixture	—	—	—	500	G's
Mechanical Vibration		Per Mil-STD-883D, Method 2007.2 Condition A, 20-2000 Hz	—	—	—	15	G's
Weight	—	—	—	—	11.2	—	grams
Relative Humidity	—	Non-condensing	—	0	—	95	%


*See Thermal Derating chart. **The PT6305 Series can be easily paralleled to provide output current in multiples of 3 amps. Please contact a Power Trends' Application Engineer for the appropriate application note. **Note:** The PT6305 Series requires a 100 μF electrolytic capacitor for proper operation in all applications.

CHARACTERISTIC DATA


PT6305, 3.3 VDC

(See Note 1)

Efficiency vs Output Current




Ripple vs Output Current




Minimum Input Voltage

(See Note 2)




Thermal Derating (Ta)

(See Note 3)




Power Dissipation vs Output Current




PT6307, 2.1 VDC

(See Note 1)

Efficiency vs Output Current




Ripple vs Output Current




Minimum Input Voltage

(See Note 2)




Thermal Derating (Ta)

(See Note 3)




Power Dissipation vs Output Current




PT6308, 1.2 VDC

(See Note 1)

Efficiency vs Output Current




Ripple vs Output Current




Minimum Input Voltage

(See Note 2)




Thermal Derating (Ta)

(See Note 3)



Power Dissipation vs Output Current



Note 1: All data listed in the above graphs, except for derating data, has been developed from actual products tested at 25°C. This data is considered typical data for the ISR.

Note 2: Minimum Vin data is typical and is not guaranteed. The data corresponds to a 2% output voltage drop.


Note 3: Thermal derating graphs are developed in free air convection cooling of 40-60 LFM with no optional heat tab soldered in a printed circuit board. (See Thermal Application Notes).

Package Style 300
Suffix A, C, D, E, N, P


PACKAGE INFORMATION AND DIMENSIONS

Revised 2/11/2000


Vertical Through-Hole Mount (Suffix N & P)



Horizontal Through-Hole Mount (Suffix A & D)



Surface Mount (Suffix C & E)



Notes: (Rev.A)

- 1: All dimensions are in inches (mm).
- 2: 2 place decimals are ± 0.30 (± 0.8 mm).
- 3: 3 place decimals are ± 0.10 (± 0.3 mm).
- 4: Recommended mechanical keep out area.
- 5: Power pin connections should utilize two or more vias per input, ground and output pin.

IMPORTANT NOTICE

Texas Instruments and its subsidiaries (TI) reserve the right to make changes to their products or to discontinue any product or service without notice, and advise customers to obtain the latest version of relevant information to verify, before placing orders, that information being relied on is current and complete. All products are sold subject to the terms and conditions of sale supplied at the time of order acknowledgment, including those pertaining to warranty, patent infringement, and limitation of liability.

TI warrants performance of its semiconductor products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are utilized to the extent TI deems necessary to support this warranty. Specific testing of all parameters of each device is not necessarily performed, except those mandated by government requirements.

Customers are responsible for their applications using TI components.

In order to minimize risks associated with the customer's applications, adequate design and operating safeguards must be provided by the customer to minimize inherent or procedural hazards.

TI assumes no liability for applications assistance or customer product design. TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right of TI covering or relating to any combination, machine, or process in which such semiconductor products or services might be or are used. TI's publication of information regarding any third party's products or services does not constitute TI's approval, warranty or endorsement thereof.

Looking for pricing, stock, or lifecycle information?

Click below to explore more details on WIN SOURCE:

 [View PT6305CT](#) on WIN SOURCE

 [Texas Instruments](#) Information

Optimize Your Supply Chain with WIN SOURCE Solutions

-  Global Sourcing Solution
-  Obsolete Management
-  Cost Control Management
-  Shortage Management
-  Alternative Solution
-  Excess Inventory Management